


CX35



connectwell
THE RIGHT CONNECTION

35 sq.mm Spring Clamp Feed Through Terminal Blocks

The Spring Clamp is operated by using a screw driver to provide an access to the wire through an opening in the spring clamp. The inserted wire gets clamped on to the current bar when the screw driver is removed.

TECHNICAL DATA

Rated Voltage	1000 V
Rated Current	125 A
Housing Material	Polymide
Standard Colour	Grey
Product Function	Feed Through
Wire Entry Orientation	Top Entry
Mounting Possibility	DIN 35/DIN 35-15 Rail
Operated by	Screw Driver
Rated Surge Voltage	8 KV
Pollution Degree	3

CONNECTION DATA

Conductor Cross Section Stranded min.	6 mm ²
Conductor Cross Section Stranded max.	35 mm ²
Conductor Cross Section AWG/Kcmil min	10 AWG
Conductor Cross Section AWG/Kcmil max	2 AWG
Conductor Cross Section Stranded with Ferrule/Lug min	6 mm ²
Conductor Cross Section Stranded with Ferrule/Lug max	35 mm ²
Conductor Cross Section Solid min	6 mm ²
Conductor Cross Section Solid max	35 mm ²
Stripping Length	23 mm

DIMENSIONS

Height	59.5 mm
Height with DIN 35 x 15 mm rail	60.3 mm
Height with DIN 35 x 7.5 mm rail	67.5 mm
Length	100 mm
Width (Thickness)	16 mm


ORDERING INFORMATION

CAT. NO.	DESCRIPTION	STD. PACK
CX35	35 sq.mm Feed Through Spring Clamp Terminal Block in Grey colour	15
CX35BU	35 sq.mm Feed Through Spring Clamp Terminal Block in Blue colour	15

NOTES

The Rated current is with the use of copper (Cu) conductor/Wire

CX35



connectwell
THE RIGHT CONNECTION

RATINGS AS PER STANDARDS

STANDARDS	UL 1059	IEC/EN60947-7-1
Conductor Cross Section Stranded min.	10 AWG	6 mm ²
Conductor Cross Section Stranded max.	2 AWG	35 mm ²
Rated Voltage	600 V	1000 V
Rated Current	115 A	125 A